16 poles + 🖶 16A - 400V CN size "77.27" inserts, enclosures: screw terminal connections standard page: 198 ÷ 202

| page. | |
|-------|-------------------------|
| page: | 208 |
| page: | 209 |
| page: | 210 |
| nade. | 258 ÷ 259 |
| | page: page: page: |

features according to EN 61984:
16A 400V 4kV 2
UL, CSA, CCC, GL certified


description

- for maximum current load, see the insert load curve section on page 31

indirect, with plate 1) female inserts with female contacts male inserts with male contacts indirect, with plate 1), use in up to 180 $^\circ\text{C}$ female inserts with female contacts, brown male inserts with male contacts, brown

1) for non-prepared conductors

CNF ...



CNF 16 RY CNM 16 RY dimensions in mm

> 77.5 27

М

F



contacts side (front view)

| F | М |
|---|--|
| ତ ⊕ ତ ∕ | P ⊕ € |
| □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ | ∫-● ●◎ ,∾● ●≅ |
| | , and an |
| α ∓ ● ● ∽ | Line en 4€ en |
| 5 ● ● -~ | |
| | |

- inserts with plate, for section conductors:

0.75 ÷ 2.5 mm² - AWG 18 ÷ 14

- torsion couple recommended for conductor fastening screws and stripping lenght see section feature of inserts on page 13

dimensions indicated are not binding and may be changed without notice